There are several notes I need to provide to aid you with the enclosed package. The original kits used 1/16" balsa. Since I wanted to print these directly on balsa sheet I developed the parts for 1/32" balsa sheet. My printer will handle up to 1/20" sheet, but I find 1/32" is a little easier to handle in the printer. As a result, some of the parts have been drawn to allow for cross grain laminations. The fuselage formers are a good example. The fin as also been drawn with a mirror image to allow for markings on both sides. This works fine as long as you are using 1/32" sheet stock.

I like to use a removable nose for winding. The parts have been drawn with this in mind. The nose former has been drawn so a removable nose plug can be used. A colored nose plug has also been drawn. For the P-40, you need a thick nose plug to get the thrust bearing in the proper location for the prop and spinner. Back the colored nose piece with a piece of 3/16" balsa. This assembly will then plug into the opening formed by the fuselage structure. I like to use a Peck thrust bearing for 1/32" prop shafts in the removable nose plug.

When using 1/32" sheet for the fuselage sides, I was concerned about the load of a fully wound motor on the rear motor peg. I like to use a piece of 3/32" aluminum tubing for the rear peg. Makes holding the model in a winding stooge very easy. To create a bit more strength at the rear peg, I apply a 3/8" diameter disk of 1/64" plywood to the inside of each fuselage side at the peg location. This has proven to be plenty strong for a fully wound motor of 1/8" Tan II rubber. A piece of 3/32" OD aluminum tubing is used for the rear motor peg.

The landing gear parts for the P-40 have been drawn per the original kit. Mirrored parts have also been drawn to allow sandwiching the landing gear legs between the 1/32" balsa parts. This makes a nicer looking installation and is quite strong. The location of the gear legs has been printed on each wing panel. You will see a line with a circle on one end. Push the landing gear wire through the printed circle. The bent wire will line up with the printed line.

The original kits came with a vacuum canopy and an injection molded spinner. A drawing has been provided that will allow you to develop forms for making your own vacuum formed parts. The original kit spinner came in red plastic.

I do hope you build and enjoy a model from this plan package.

Paul Bradley























novel, follow inese char siers:





